



Model Number


G12/GV12/37/40b/92

Thru-beam sensor
with 4-pin, M12 x 1 connector


Features

- Basic Series with M12 metal housing for standard applications
- Robust M12 threaded housing
- Visible red light
- Light/dark ON, programmable


Dimensions



Electrical connection



Pinout



Release date: 2013-11-19 15:35 Date of issue: 2013-11-19 08:49:42_eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group
www.pepperl-fuchs.com

USA: +1 330 486 0001
fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411
fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091
fa-info@sg.pepperl-fuchs.com

Technical data**System components**

| | |
|----------|----------------|
| Emitter | G12/92 |
| Receiver | GV12/37/40b/92 |

General specifications

| | |
|---------------------------|--------------------------------------|
| Effective detection range | 0 ... 5000 mm |
| Adjustment range | 250 ... 5000 mm |
| Reference target | receiver |
| Light source | LED |
| Light type | modulated visible red light , 660 nm |
| Optical face | frontal |
| Ambient light limit | 20000 Lux |

Indicators/operating means

| | |
|--------------------|-----------------------------------|
| Function indicator | LED yellow: switching state |
| Control elements | sensitivity adjustment , receiver |

Electrical specifications

| | | |
|--------------------------------|-------|----------------|
| Operating voltage | U_B | 10 ... 30 V DC |
| Ripple | | 10 % |
| No-load supply current | I_0 | ≤ 20 mA |
| Time delay before availability | t_v | ≤ 25 ms |

Input

| | |
|---------------|------------------------------|
| Control input | light on +UB dark on: 0 V |
|---------------|------------------------------|

Output

| | | |
|---------------------|---|---------------|
| Switching type | light/dark on | |
| Signal output | 1 PNP output, short-circuit protected, reverse polarity protected, open collector | |
| Switching voltage | max. 30 V DC | |
| Switching current | max. 300 mA | |
| Voltage drop | U_d | ≤ 3 V |
| Switching frequency | f | ≤ 500 Hz |
| Response time | | ≤ 1 ms |

Standard conformity

| | |
|-----------|--------------|
| Standards | EN 60947-5-2 |
|-----------|--------------|

Ambient conditions


| | |
|---------------------|--------------------------------|
| Ambient temperature | -25 ... 55 °C (-13 ... 131 °F) |
| Storage temperature | -40 ... 70 °C (-40 ... 158 °F) |

Mechanical specifications

| | |
|-------------------|--------------------------|
| Protection degree | IP67 |
| Connection | connector M12 x 1, 4-pin |
| Material | |
| Housing | brass, nickel-plated |
| Optical face | PMMA |
| Mass | 15 g (device) |

Approvals and certificates

| | |
|--------------|--|
| CCC approval | CCC approval / marking not required for products rated ≤ 36 V |
| Approvals | CE |

Curves/Diagrams**Accessories****BF 12**

Mounting flange, 12 mm

BF 12-F

Mounting flange with dead stop, 12 mm

BF 5-30

Universal mounting bracket for cylindrical sensors with a diameter of 5 ... 30 mm


V1-G-2M-PUR

Female cordset, M12, 4-pin, PUR cable

V1-W-2M-PUR

Female cordset, M12, 4-pin, PUR cable

Additional accessories can be found in the Internet.



Release date: 2013-11-19 15:35 Date of issue: 2013-11-19 08:49:42_eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group
www.pepperl-fuchs.com

USA: +1 330 486 0001
fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 4411
fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091
fa-info@sg.pepperl-fuchs.com